

















**Catalog LP01ENe** 

# **Linear Products**



AxialPower Series 🔷

**Linear** •

**Drives**  $\circ$ 

SA-Series (

DA-Series (

SC-Series



For over 60 years, ElectroCraft has been helping engineers translate innovative ideas into reality – one reliable motor at a time. As a global specialist in custom motor and motion technology, we provide the engineering capabilities and worldwide resources you need to succeed.





This guide has been developed as a quick reference tool for ElectroCraft products. It is not intended to replace technical documentation or proper use of standards and codes in installation of product.

Because of the variety of uses for the products described in this publication, those responsible for the application and use of this product must satisfy themselves that all necessary steps have been taken to ensure that each application and use meets all performance and safety requirements, including all applicable laws, regulations, codes and standards.

Reproduction of the contents of this copyrighted publication, in whole or in part without written permission of ElectroCraft is prohibited.

Designed by media & brands  $\cdot$  www.media-brands.de

۷۶		

⊴	

-	

# **Table of Contents**

Typical Applications .								3
Which Linear Product								5
Drive Product Matrix								6

AxialPower Plus Stepper	٠	 	 7
APPS11M		 	 7
APPS17		 	 9
APPS23		 	 11





A-Seri	ies	5.															1	9
SA45																	. 1	9
SA49																	. 2	21

DA-Series												23
DA43												. 23
DA47												. 25

SC-Series									27
SCA-L			 						. 2
SCA-S			 						. 2

System Matrix								31
Other Products								33
Orives Accessories.								36







sales@electromate.com



# Typical applications for

# **ElectroCraft Linear Products:**

- Custom OEM applications (Our Specialty)
- Packaging
- Semiconductor handling and testing
- Antenna positioning
- Laboratory equipment
- Rapid prototyping machines
- Medical equipment
- Dispensing





An ElectroCraft linear actuator with a custom mechanical configuration helps keep liquid and this business flowing.

# **Medical Dispensing Pump**

Situation: An existing ElectroCraft customer wished to expand their line of medical dispensing pumps. Critical performance metrics included linear speed, axial force, and precise linear positioning. The customer required a wide range of output performance and input power requirements to successfully complete the "family" product offering.

**Solution:** ElectroCraft was able to design custom windings for the complete linear product offering combining both the linear actuator and leadscrew motor configurations, reducing the number of parts required yet still cover the customer's broad range of linear speed, force, and positioning requirements.

Results: ElectroCraft was able to reduce inventories through design and combined this effort with a Lean manufacturing based pull-system and Kanban program to further reduce inventory while improving delivery performance regardless of the customer's fluctuations in demand.

# **Helicopter Autopilot**

**Situation:** A manufacturer interested in introducing a completely new technology of autopilot system approached ElectroCraft for an innovative solution. Positional accuracy was critical in this application. The customer was looking for a collaborative effort into the design of the electro-mechanical device.

**Solution:** ElectroCraft modified a size 17 Linear Actuator with a custom Mil-spec cable assembly, special lead-screw insert and lubrication in order to deliver prototypes quickly. Further collaboration with our customer's innovative R&D team improved the overall performance on subsequent design iterations.



ElectroCraft helps steer the way for a new generation of helicopter auto-pilot systems.

**Results:** The customer is flying high. Their concept is turned into reality as their product is being final tested and approved for flight.



The pressure is on this high powered linear actuator at the heart of this analytical instrument.

# **Chromatography Platform**

**Situation:** A leading manufacturer of high end chromatography instruments needed a cost effective solution for a high pressure requirement in a new platform chromatography instrument.

**Solution:** ElectroCraft incorporated ballscrew technology into our most powerful 34 frame Linear Actuator to produce a compact, yet powerful product. Capable of generating over 900 pounds of force, this linear actuator integrates a high precision ball-nut into the rotor assembly with the ballscrew providing the positional accuracy and the high linear force needed to generate pressures in excess of 15,000 psi.

Sold & Service By: The capability of the high force and compact linear actuator allowed the customer to expand their product into new markets and opportunities for their customer base.

Toll Free Phone (877) SERVID98



Select your Linear Products!





A true Push-Pull, axially translating screw.



Rotating screw with an axial translating external nut.

# Guided Linear Actuator



#### Functionality:

Some linear applications do not restrict the leadscrew from rotating

The Guided Linear Actuator feature restricts the screw from rotating, allowing the leadscrew to translate axially

A mechanical assist to the linear actuator to restrict the leadscrew from rotating with the rotor.

# **Drive Product Matrix**

	Bipolar Ste	pper Drive		PM	IDC Servo Dr	ive	
	SA4505	SA4510	DA4303	DA4709	DA4718	SCA-LS-30-03	SCA-SS-30-06
Product Description							
See on page	19	21	23	25	25	27	29
Power Features							
Min. Voltage (VDC)	11	11	11	11	11	11	11
Max. Voltage (VDC)	48	48	30	70	70	30	30
Dual Bridge MOSFET Driver	•	•	•	•	•	•	•
Switching Frequency (kHz)	50	50	Linear	50	50	50	50
Linear Output			•			•	
PWM Output				•	•		•
Trap Waveform				•	•		•
Power Ratings							
Peak Current	5	10	3	18	36	3	6
Nominal Current	5	10	3	9	18	3	6
Adjustable Current	•	•	•	•	•	•	•
Max Continuous Power (W)	240	480	75	1260	2520	75	150
Control Modes							
Max. Step Input Frequency (kHz)	40	40					
Microstepping up to 1/16	•	•					
Internal Oscillator (x8)	•	•					
External Pulse Train (5-24 Logic)	•	•					
Fallback Current	•	•					
Analog Command (VDC)	+1 to +5 VDC	+1 to +5 VDC	±10	±10	±10	±10	±10
Torque Control				•	•	•	•
I/R Compensation			•	•	•	•	•
Speed Control using Tach			•	•	•	•	•
Speed Control using Voltage			•	•	•	•	•
Speed Control using Encoder							
Communication / Compliance							
CE Compliance (LV Directive)	•	•	•	•	•	•	•
Physical Enclosure							
Totally Enclosed	•	•	•	•	•	•	•
Case Type	Book Shelf	Book Shelf	Book Shelf	Book Shelf	Book Shelf	Rack	Rack





sales@electromate.com


# **APPS11M: ElectroCraft AxialPower™ Plus** | Linear Actuator Stepper

Size	Holding Torque oz-in (Ncm)	Linear Speed inch / sec (mm / sec)	Linear Force Pounds (Newton)
NEMA 11, 1.8°	14 (10)	16 (400)	32 (140)



#### Reliable. Precise.

The ElectroCraft size 11 stepper-based linear actuator is ultra-reliable and made to exacting standards incorporating precision materials all designed to provide reliable performance with axial resolution in the microns.





Step 2: APPS11M Torque and Mechanical Data (Bipolar) APPS11M-7 APPS11M-10 Step Angle = 1.8°, 9.5 oz-in hold torque Supply = 48 VDC X 1 amp/phase Step Angle = 1.8°, 9.5 oz-in hold torque Supply = 48 VDC X 1 amp/phase = 24 VDC X 1 amp/phase = 24 VDC X 1 amp/phase 35 156 35 156 30 30 132 132 25 110 25 110 88 20 88 20 Poun Poun 15 66 15 66 10 44 10 22 5 22 5 M D M 4 (100) 8 (200) 12 (300) 16 (400) 4 (100) 8 (200) 12 (300) 16 (400) Speed, inch (mm) / second @ 48VDC Speed, inch (mm) / second @ 48VDC 6 (150) 0 2 (50) 4 (100) 6 (150) 8 (200) 2 (50) 4 (100) 8 (200) Speed, inch (mm) / second @ 24VDC Speed, inch (mm) / second @ 24VDC Curves are approximaned as straight line for ease of use. Thread Designation Thread Lead Inches (mm) / Rev Linear Travel Inch (mm) / Full-Step 3/16-20 ACME (1S) 0.050 (1.3) 0.00025 (0.0064) 3/16-24 ACME (3S) 0.125 (3.2) 0.00063 (0.0160)

0.333 (8.5)

Example "L" thread pitch: @ 2 in/sec = 6,350 halfsteps/sec

0.00167 (0.0424)

Ste	р 3:			Available Wind	dings		
	Metric	7A05	7A10	7A15	10A05	10A10	10A15
L	Current Bipolar (A/Phase)	0.5	1.0	1.5	0.5	1.0	1.5
Bipolar	Phase Voltage VDC	5.0	2.5	1.7	6.2	3.1	2.1
B	Phase Resistance (ohm)	10.00	2.50	1.10	12.40	3.10	1.40
	Phase Inductance (mH)	6.8	1.5	0.7	10.4	2.7	1.1

Unipolar windings available upon request.

3/16-24 ACME (8S)



Still need help?
Easily build your own motor at www.configureamotor.com



Need an anti-backlash feature or don't see exactly what you need? Have ElectroCraft build you a custom winding, stack length or fully customized linear product ... that's our specialty!



# APPS17 & APPS17M: ElectroCraft AxialPower™ Plus | Stepper


Size	Holding Torque oz-in (Ncm)	Linear Speed inch / sec (mm / sec)	<b>Linear Force</b> Pounds (Newton)
NEMA 17, 1.8°	47 (33)	20 (508)	70 (310)





#### Precise. Quick.

The ElectroCraft NEMA 17 stepper-based linear actuator is reliable, made to be both precise and responsive with positional accuracy in the microns, load capabilities up to 70 Lbs (32kg), and linear speeds to 12 inches/second (305mm/second).





Step 2: APPS17 & APPS17M Torque and Mechanical Data (Bipolar) APPS17-29 APPS17-47 APPS17M-33 APPS17M-21 Supply = 40 VDC x 2 amp/phase = 24 VDC x 2 amp/phase Supply = 40 VDC x 2 amp/phase = 24 VDC x 2 amp/phase 50 225 80 360 70 315 180 40 60 270 50 225 30 135 Pounds 40 180 20 90 135 30 20 10 10 В 5 (125) 10 (250) 15 (375) 20 (500) 5 (125) 10 (250) 15 (375) 20 (500) Speed, inch (mm) / second @ 40VDC ed, inch (mm) / second @ 40VDC 3 (75) 6 (150) 9 (225) 12 (300) 0 3 (75) 6 (150) 9 (225) 12 (300) Speed, inch (mm) / second @ 24VDC Speed, inch (mm) / second @ 24VDC 29A20 (21A20) Curves are approximaned as straight line for ease of use. 47A20 (33A20) Thread Designation Thread Lead Inches (mm) / Rev Linear Travel Inch (mm) / Full-Step Y Intercept Pounds (N) X Intercept 24 Volt X Intercept 40 Volt Y Intercept Pounds (N) X Intercept 24 Volt X Intercept 40 Volt 0.02500 0.00013 40 1 35 2 25 80 1.00 1 68 J\* 1/4-40 UN (1S) (0.6)(0.0033)(180)(35)(60)(355)(25)(40)0.03125 0.00016 38 1.69 2.81 76 1.25 2.12 ٧× 1/4-32 ACME (1S) (170)(340)(30)(0.8)(0.0041)(40)(70)(55)0.05000 0.00025 37 4 50 74 2.00 3.38 2.70 E\* 1/4-20 ACME (1S) (1.3)(0.0064)(165)(70)(115)(330)(50)(85)0.06250 0.00031 36 3.37 5.62 72 2.55 4.25 Α 1/4-16 ACME (1S) (1.6)(0.0079)(160)(85)(140)(320)(65)(110)0.12500 0.00063 6.75 11.25 5.00 8.44 30 60 В 1/4-16 ACME (2S) (3.2)(0.0160)(135)(170)(285)(265)(130)(215)0.20000 0.00100 24 10.80 18.00 48 8.12 13.50 F\* 1/4-20 ACME (4S) (105)(460)(205)(340)(5.1)(0.0254)(275)(215)0.25000 0.00125 20 13.50 22.5 40 10.12 16.88 1/4-16 ACME (4S) (6.4)(0.0318)(90)(340)(570)(175)(260)(430)

Motor step rate calculation: Motor step rate (halfstep/sec) = [Speed (in/sec)\*2] / [travel (in/fullstep)]

Example "B" thread pitch: @ 2 in/sec = 6,420 halfsteps/sec

Step 3: Available Windings							
	Imperial	29A10	29A15	29A20	47A10	47A15	47A20
	Metric	21A10	21A15	21A20	33A10	33A15	10A20
Bipolar	Current Bipolar (A/Phase)	1.0	1.5	2.0	1.0	1.5	2.0
<u>ia</u>	Phase Resistance (ohm)	3.8	1.90	0.95	4.9	2.4	1.2
	Phase Inductance (mH)	4.8	2.3	1.2	9.1	4.9	2.3

Unipolar windings available upon request.

<sup>\*</sup> Consult factory for availability.



Still need help?
Easily build your own motor at www.configureamotor.com



Need an anti-backlash feature or don't see exactly what you need? Have ElectroCraft build you a custom winding, stack length or fully customized linear product ... that's our specialty!



# **APPS23 : ElectroCraft AxialPower™ Plus** | Linear Actuator Stepper


Size	Holding Torque oz-in (Ncm)	Linear Speed inch / sec (mm / sec)	Linear Force Pounds (Newton)
NEMA 23, 1.8°	150 (106)	7.5 (190)	175 (780)





## Quick. Powerful.

The ElectroCraft NEMA 23 stepper-based linear actuator is reliable, made to be both responsive and powerful, with positional accuracy in the microns, load capabilities up to 175 Lbs (80kg) and linear speeds to 5 inches/second (130mm/second).





#### Step 2: APPS23 Torque and Mechanical Data (Bipolar) APPS23-90 APPS23-150 Step Angle = 1.8°, 90 oz-in hold torque Supply = 80 VDC X 3 amp/phase Step Angle = 1.8°, 90 oz-in hold torque Supply = 80 VDC X 3 amp/phase = 40 VDC X 3 amp/phase = 40 VDC X 3 amp/phase 120 540 175 777 150 666 100 450 125 555 80 360 100 444 60 270 ĕ 75 333 40 180 50 222 20 90 25 111 Q S 2 (50) 4 (100) 6 (150) 8 (200) 2 (50) 4 (100) 6 (150) 8 (200) Speed, inch (mm) / second @ 80VDC Speed, inch (mm) / second @ 80VDC 1 (25) 2 (50) 3 (75) 4 (100) 0 1 (25) 2 (50) 3 (75) 4 (100) Speed, inch (mm) / second @ 40VDC Speed, inch (mm) / second @ 40VDC 90A30 Curves are approximaned as straight line for ease of use. 150A30 Thread Designation Thread Lead Inches (mm) / Rev Linear Travel Inch (mm) / Full-Step Y Intercept Pounds (N) X Intercept 24 Volt X Intercept 40 Volt Y Intercept X Intercept 24 Volt X Intercept 40 Volt Pounds (N) 0.050 0.00025 109 2.8 5.6 157 19 3.8 3/8-20 ACME (1S) Q (1.3)(0.0064)(30)(72)(145)(44)(50)(95) 0.063 0.00031 104 3.5 7.0 151 2.3 4.7 T\* 3/8-16 ACME (1S) (29)(90)(180)(60)(120)(1.6)(0.0079)(42)0.063 0.00042 97 47 94 142 3.1 6.3 W 3/8-12 ACME (1S) (1.6)(0.0107)(26)(120)(240)(40)(80)(160)0.100 0.00050 92 5.6 11.2 130 3.8 7.5 S 3/8-10 ACME (1S) (190)(2.5)(0.0127)(26)(145)(285)(36)(95)0.167 0.00083 75 9.4 18.8 106 6.3 12.5 $\mathsf{L}^{\star}$ 3/8-12 ACME (2S) (4.2)(0.0211)(21)(240)(475)(30)(160)(320)

Motor step rate calculation: Motor step rate (halfstep/sec) = [Speed (in/sec)\*2] / [travel (in/fullstep)]

Example "S" thread pitch: @ 2 in/sec = 8,000 halfsteps/sec

Step 3: Available Windings							
	Imperial	90A10	90A20	90A30	150A10	150A20	150A30
	Current Bipolar (A/Phase)	1.0	2.0	3.0	1.0	2.0	3.0
Bipolar	Phase Voltage VDC	5.8	3.0	1.8	7.9	3.8	2.4
B	Phase Resistance (ohm)	5.78	1.50	0.60	7.92	1.90	0.80
	Phase Inductance (mH)	20.3	5.2	2.0	35.0	8.6	3.5

Unipolar windings available upon request.



Still need help?
Easily build your own motor at www.configureamotor.com



Need an anti-backlash feature or don't see exactly what you need? Have ElectroCraft build you a custom winding, stack length or fully customized linear product ...

that's our specialty!

<sup>\*</sup> Consult factory for availability.



# L3S: ElectroCraft 34 Frame | Linear Actuator Stepper

Size	Holding Torque oz-in (Ncm)	Linear Speed inch / sec (mm / sec)	<b>Linear Force</b> Pounds (Newton)
NEMA 34, 1.8°	396 (280)	8.75 (225)	700 (3120)







#### Powerful. Robust.

This NEMA 34 stepper-based linear actuator is the workhorse of linear motors. Made to move your most demanding loads with dual front bearings capable of up handling 700 Lbs (320kg) of linear force with precise resolution is a performance to be respected.



Step 1:	Step 1: L3S Frame Size Drawing Key										
					Α	В	С	D	Е	F	G
Model	Length	Weight	Holding Torque	Roter Inertia	Pilot Length	Pilot Diameter	Mount Hole Callout	Mount Hole Spacing	External Flange Dimension	External Nut Thread	Screw End Mod
L3S-90	3.04 in (77.2 mm)	65 oz (1.8 kg)	396 oz-in (280 Ncm)	0.002 oz-in-sec² 2.8-² Ncm-sec²	0.08 in (2 mm)	2.875 ±0.001 in (73 ±0.025 mm)	0.260 ±0.01 in dia (6.6 ±0.25 mm dia)	2.74 in (69.6 mm)	3.38 in (86 mm)	M17 x 1.0	1/4-28 UNF M6 x 1.0 0.2502 / 0.2499 in dia Journal







#### Step 2: L3S Torque and Mechanical Data (Bipolar) L3SA Step Angle = 1.8°, 396 oz-in hold torque Supply = 80 VDC X 3 amp/phase = 40 VDC X 3 amp/phase 700 3150 600 2700 500 2250 400 1800 300 1350 200 900 100 450 G F 8 (200) 2 (50) 4 (100) 6 (150) Speed, inch (mm) / second @ 80VDC 3 (75) 0 1 (25) 2 (50) 4 (100) Speed, inch (mm) / second @ 40VDC

	Thread Designation	Thread Lead Inches (mm) / Rev	Linear Travel Inch (mm) / Full-Step
G	1/2-20 ACME (1S)	0.05 (1.3)	0.00025 (0.0064)
А	1/2-10 ACME (1S)	0.10 (2.5)	0.00050 (0.0127)
F	1/2-10 ACME (2S)	0.20 (5.1)	0.00100 (0.0254)

Curves are approximaned as straight line for ease of use.

Example "A" thread pitch: @ 2 in/sec = 8,000 halfsteps/sec

Ste	p 3:		Available Windings		
	Imperial	M200	M300	M500	
L	Current Bipolar (A/Phase)	2.0	3.0	5.0	
Bipolar	Phase Voltage VDC	5.0	3.0	2.0	
B	Phase Resistance (ohm)	2.50	1.00	0.40	
	Phase Inductance (mH)	21.9	8.7	3.4	

Uniploar winding available for OEM application upon request.



Still need help?
Easily build your own motor at www.configureamotor.com



Need an anti-backlash feature or don't see exactly what you need? Have ElectroCraft build you a custom winding, stack length or fully customized linear product ... that's our specialty!



# APPD15 & APPD15M: ElectroCraft AxialPower™ | Linear Actuator PMDC


Size	Peak Torque oz-in (Ncm)	Linear Speed inch / sec (mm / sec)	<b>Linear Force</b> Pounds (Newton)
15 FRAME	45 (32)	2.5 (64)	70 (315)







#### Simple. Direct.


The ElectroCraft 15 frame PMDC based linear actuators offers a simple on/off control for direct axial movement. Whether replacing an air cylinder, or introducing a simple electric actuator to your system, this simple, low cost solution is a reliable alternative.











Step 3:	Available Windings
Imperial	15V12
Metric	11V12
Voltage (Vdc)	12.0
Voltage Constant V/kRPM	3.2
Torque Constant oz-in/A (Ncm/A)	4.3 (3)
Max Continuous Current (A)	3.7
Peak Current (A)	10.0

<sup>\*24</sup> Volt windings for OEM applications are available upon request.



Still need help?
Easily build your own motor at www.configureamotor.com



Need an anti-backlash feature or don't see exactly what you need? Have ElectroCraft build you a custom winding, stack length or fully customized linear product ... that's our specialty!




# APPD25 & APPD25M: ElectroCraft AxialPower™ | Linear Actuator PMDC

Size	Peak Torque	Linear Speed	<b>Linear Force</b>
	oz-in (Ncm)	inch / sec (mm / sec)	Pounds (Newton)
25 FRAME	215 (152)	1.6 (40)	180 (810)




## Simple. Direct.

The ElectroCraft 25 frame PMDC based linear actuators offers a simple on/off control for direct axial movement. Whether replacing an air cylinder, or introducing a simple electric actuator to your system, this simple, low cost solution is a reliable alternative.







Step 3:	Available Windings			
Imperial	25V12*	25V24		
Metric	18V12*	18V24		
Voltage (Vdc)	12.0	24.0		
Voltage Constant V/kRPM	3.3	6.6		
Torque Constant oz-in/A (Ncm/A)	4.4 (3.1)	8.9 (6.2)		
Max Continuous Current (A)	9.2	4.6		
Peak Current (A)	32.0	16.0		

<sup>\* 12</sup> Volt windings for OEM applications are available upon request. More coarse threads (increased speed).



Still need help?
Easily build your own motor at www.configureamotor.com



Need an anti-backlash feature or don't see exactly what you need? Have ElectroCraft build you a custom winding, stack length or fully customized linear product ... that's our specialty!




# **SA45**: **Electrocraft CompletePower™** | Stepper Drive

Power Supply Nomi	Nominal	Phases	Operation	on Mode	Special Functions			
Voltage	Current		Fullstep	Micro stepping	Integrated Oscillator	Current Fallback	Anti-Resonance Anti-Noise	
11 - 48	5 / 10	2	•	•	•	•	•	



#### For Stepper Motors. Up to 480W.

This bipolar stepper drive provides microstepping to 1/16 built into a fully enclosed rugged aluminum case. It can be DIN-rail mounted or panel mounted for fast integration. The mode of operation is set by simple DIP switches. Features include an internal oscillator that allows operation of the drive at a internal speed set point or with an external analog speed reference that can scale this set point. Both the 5 A and 10 A versions of this drive can be powered by the same range of voltage supplies. This drive is protected against over-current and overtemperature and incorporates the state of the art dual full bridge MOSFET driver for maximum efficiency. Connectivity is tool-free with RJ45-CAT5 plugs for the control inputs and push-type terminals for power.



		SA45 S	pecifications						
Model Number	Power Supply Voltage (VDC)	Nominal Current (Amps)	Max. Power with Heatsink (Watts)	Frequency of power output stage (kHz)	Efficiency (%)				
SA4505	11 - 48	5	240	50	95				
SA4510	11 - 48	10	480	50	95				
		Cor	itrol Inputs						
	Enable			Optical, Ri = 1 kOhm; max. 20 r	mA				
	Direction			Optical, Ri = 1 kOhm; max. 20 r	mA				
	Step		Optical, Ri = 1 kOhm; max. 20 mA; 250 kHz						
	Speed ext.		+1to +5 VDC; Ri = 100 kOhm						
		9	switches						
	Microstep			1/1; 1/2; 1/4; 1/16					
	Current			0,5 A to 5 A / 1 A to 10 A					
	Fallback			on / off					
	Oscillator			on / off					
	Oscillator x8			on / off					
			Outputs						
	Auxiliary voltage source	+5V		+5 VDC / 50 mA					
	Fault			Optical, max. 20 mA					
			Display						
	LEDs			green= Power / red = Error					
		Function o	of Potentiometers						
	Speed		Ra	Range: 4 Hz - 500kHz / 40 Hz - 4800 Hz					
		Ambie	nt conditions						
	Operation temperature	(°C)		-10 to +45					
	Storage temperature (°C)			-40 to +85					
	Humidity Range Not Condens	sing (%rel)		20 to 80 % rel.					
		Mode	of Operation						

	Available Accessories for SA45 (details see page 36)											
IA210x	CAxxx HA3008 HA3018 HA3028 MA0025 WA2											
<u>o</u> <u>o</u>	Q		0									

Fullstep; Microstep: 1/2, 1/4, 1/16




# **SA49 : Electrocraft CompletePower™** | Stepper Drive

Power Supply Nominal	Iominal Phases		on Mode	Special Functions			
Voltage	Current	Triases	Fullstep	Micro stepping	Integrated Oscillator	Current Fallback	Anti-Resonance Anti-Noise
24 - 90	5	2	•	•	•	•	•



#### For Stepper Motors. Up to 450W.

This bipolar stepper drive provides microstepping to 1/16 built into a fully enclosed rugged aluminum case. It can be DIN-rail mounted or panel mounted for fast integration. The mode of operation is set by simple DIP switches. Features include an internal oscillator that allows operation of the drive at a internal speed set point. The current setting, internal speed and ramp time can easily be selected using BCD input switches then toggled into memory. This drive is protected against over-current and over-temperatureand incorporates the state of the art dual full bridge MOSFET driver for maximum efficiency. Connectivity is tool-free with RJ45-CAT5 plugs for the control inputs and push-type terminals for power.





		SA49 S	pecifications					
Model Number	Power Supply Voltage (VDC)	Nominal Current (Amps)	Max. Power with Heatsink (Watts)	Frequency of power output stage (kHz)	Efficiency (%)			
SA4905	24 - 90	5	450	50	95			
		Con	trol Inputs					
	Enable			Optical, Ri = 1 kOhm; max. 20	D mA			
	Direction			Optical, Ri = 1 kOhm; max. 20	O mA			
	Step (250 kHz)			Optical, Ri = 1 kOhm; max. 20	O mA			
		S	witches					
	Microstep			1/1; 1/2; 1/4; 1/16				
	Current Set			idle / set				
	Fallback			on / off				
	Speed Set			idle / set				
	I/O voltage			int / ext				
	Enable			int / ext				
	BCD Select			Speed / Current / Ramp				
		(	Dutputs					
	Auxiliary voltage source	e +5V		+5 VDC / 50 mA				
	Fault			Optical, max. 20 mA				
			Display					
	LEDs			green = Ready / red = Erro	or			
		Function c	f Potentiometers					
	Speed			nge: 1,5 Hz - 1,2 kHz / 12 Hz -	9,6 kHz			
			nt conditions					
	Operation temperature	e (°C)		-10 to +45				
	Storage temperature	(°C)		-40 to +85				
	Humidity Range Not Conder	nsing (%rel)		20 to 80 % rel.				

#### Mode of Operation

Fullstep; Microstep: 1/2, 1/4, 1/16

The information on these pages represents data that is preliminary in nature and is subject to change. Please contact the factory for the most current information.



	Available Accessories for SA49 (details see page 36)											
IA210x	CAxxx	xx HA3008 HA3018 HA3028 MA0025 WA250										
<u></u>	Q		0									




# DA43 : Electrocraft CompletePower™ | Servo Amplifier

Power Supply	Naminal	0	Operation Mode						
Power Supply Voltage	Nominal Quadrants Current	Quadrants	Torque Control	Analog	Speed Control				
				Pos.	I x R Comp.	DC-Tacho	Voltage	Encoder	
11 – 30	3	4	•		•		•		



#### For Brush-Commutated Linear PMDC Motors. Up to 75 W.

This servo-amplifier is built into a fully enclosed rugged miniature aluminum case. Linear servo amplifiers are ideal for low friction applications requiring high bandwidth, low noise and minimal distortion from the power electronics. The drive can be configured in the following modes of operation with simple dip switch settings: I/R compensation, Tach mode, Voltage mode and Torque mode. Input power of 30 VDC combined with a mountable heat-sink provides up to 75 Watts of power. Inputs include current limit, max set value and gain functions. The drive handles continuous currents up to 3 A. The linear power stage is protected against overcurrent and over-temperature.





**DA43 Specifications** Model Power Supply Voltage Aux. Voltage Verror Nominal Current Max. Power with Efficiency Number (VDC) (VDC) (Amps) Heatsink (Watts) (%) DA4303 11 - 30 5 - 30 75 97 **Control Inputs** Set value -10 to +10 VDC; Ri = 20 kOhm lmax 0 to +10 VDC; Ri > 10 kOhm max. 50 VDC; Ri = 75 kOhm Tacho Enable TTL/ +24 VDC; Ri = 47 kOhm Ramp active LO; Ri = 100 kOhm **Switches** Tacho-, Voltage-, IxR-, Torque-Mode Not set / Set Set value via Offset extern / intern Outputs Auxiliary voltage source +10 VDC / 10 mA each Auxiliary voltage source +10 VDC / 10 mA each Error TTL / 24 VDC; Ri = 50 Ohm Display LEDs green = Power / red = Error Potentiometers Function of Potentiometer Offset; nmax; Gain; IxR; Imax Ambient conditions Operation temperature (°C) -10 to +45 Storage temperature (°C) -40 to +85 Humidity Range Not Condensing (%rel) 20 to 80 % rel. Mode of Operation Speed-control by voltage Torque-control IxR-compensation Speed-control by DC-tacho

Available Accessories for DA43 (details see page 36)												
ASO-BM-70-30	CAxxxx	MA0025	WA2509									
	Q											
HA2008	HA	2018	HA2028									




# **DA47 : Electrocraft CompletePower™** | Servo Amplifier

Power Supply	Naminal		Operation Mode						
Power Supply Voltage		Torque	Analog	Speed Control					
_			Control	Pos.	I x R Comp.	DC-Tacho	Voltage	Encoder	
11 – 70	9 / 18	4			•	•	•		



#### For Brush-Commutated PMDC Motors. Up to 1260 W.

This four-quadrant PWM brush DC servo amplifier is fully enclosed in a small, rugged aluminum case which can be DIN-rail mounted or panel mounted for easy integration. The drive can be configured in the following modes of operation with simple dip switch settings: I/R compensation, Tach mode, Voltage mode and Torque mode. Both the 9 A and 18 A versions have twice the rated current available as peak current for intermittent overload conditions. This drive is protected against over-current and over-temperature and incorporates state of the art MOSFET technology for maximum efficiency. Connectivity is tool-free with RJ-45-connectors for input/outputs and push-type terminals for supply power and motor connections.





			DA47	Specification	S					
Model Number	Power Supply Voltage (VDC)	Aux. Voltage Verror (VDC)	Nominal Current (Amps)	Peak current (Amps)	Max. Power with Heatsink (Watts)	Frequency of power output stage (kHz)	Efficiency (%)			
DA4709			9	18	630					
DA4718	11 - 70	5 - 30	18	36	1260	50	95			
			Co	ntrol Inputs						
		Set value			-10 to +10	O VDC; Ri = 20 kOhm				
		Tacho			max. 50	VDC; Ri = 50 kOhm				
		Enable			TTL/ +24	VDC; Ri = 4.7 kOhm				
		l Limit			in	itern / extern				
		Ramp		TTL / +24 VDC; Ri = 4.7 kOhm						
		lmax			0 to +10 \	VDC; Ri > 100 kOhm				
				Switches						
Tacho-, Voltage-, IxR-, Torque-Mode					Not set / Set					
	Set v	alue via Offset			ex	xtern / intern				
		l peak				on / off				
		1.		Outputs	-	NDC (50				
		y voltage source			+5 VDC / 50 mA ±10 VDC / 20 mA					
		y voltage sources			1 / 0.5 V/A; Ri = 100 Ohm					
		Monitor I  Monitor n			0.1 V / 1 Vmotor ; Ri = 100 Ohm					
		sory output /Error				h Pull / TTL / +24V; Ri = 50 Oh	nm.			
	Supervis	ory output /Enoi		Display	Open Collector / Fusi	111 dil / 112 / +24v, id = 30 Ol				
		LEDs		Бізріаў	areen =	Power / red = Error				
			Pot	tentiometers						
	Function	of Potentiometer			Offset; nmax; Gain; lxR; lmax					
			Ambi	ent conditions						
	Operation	n temperature (°C)			-10 to +45					
	Storage	temperature (°C)			-40 to +85					
	Humidity Range	e Not Condensing (	%rel)		20 to 80 % rel.					
			Mode	e of Operation						
Speed	-control by voltage	1	orque-control	lx	R-compensation	Speed-control b	y DC-tacho			

	Available Accessories for DA47 (details see page 36)											
ASO-BM-70-30	IA210x	CAxxxx	HA3008	HA3018	HA3028	MA0025	WA2509					
	00	0		(A)	8							




# SCA-L: Electrocraft CompletePower™ | Servo Amplifier

Model	Model Power Nominal Quadrant Supply Current Voltage	Nominal	Quadrants	Operation Mode					
		To	Torque	Analog	Speed Control				
			Control	Pos.	I x R Comp.	DC-Tacho	Voltage	Encoder	
SCA-LE-30-03	11 – 30	3	4						•
SCA-LS-30-03	11 – 30	3	4	•		•	•	•	



#### For Brush-Commutated PMDC Motors. Up to 75 W.

This linear four-quadrant brushless DC servo amplifier is fully enclosed in a rugged aluminum case which can be panel mounted for easy integration. The drive is available in several configurations depending on your control requirements. The drive handles continuous currents up to 3 Amps and is protected against over-current, over-temperature and motor short-circuit.







		SCA-L Spe	cifications				
Model Number	Power Supply Voltage (VDC)	'	Nominal Current (Amps)		Max. Power with Heatsink (Watts)		
SCA-LE-30-03	44. 20						
SCA-LS-30-03	11 - 30		3		75		
		Control	Inputs				
	Set value			-10 to +10 VDC;	Ri = 100 kOhm		
Tacho max. 50 VDC; Ri = 50 kOhm							
	Enable			+8 to +30 VDC;	Ri = 5 kOhm		
	Encoder input signals (SCA-LE	only)	Channel A & /A;	3 & /B; I & /I; max. 600 k	Hz ; TTL/ +5 to +24 VDC; Ri > 10 kOhr		
		Out	outs				
A	Auxiliary voltage source for encoder (S	CA-LE only)	+5 VDC / 100 mA				
	Auxiliary voltage source		+3,9 VDC / 20 mA				
	Auxiliary voltage source		-3,9 VDC / 20 mA				
	Auxiliary voltage source Enable	· +V	Connected with 4.7 kOhm to +VCC				
	Error		Open Collector max. +30 VDC; 20 mA				
		Disp	olay				
	LEDs			green = OK /	red = Fault		
		Potentio	ometers				
	Function of Potentiometer		Gain; nmax; lmax; lxR; Offset				
		Ambient c	onditions				
	Operation temperature (°C	)	-10 to +45				
Storage temperature (°C) -40 to +85							
Humidity Range Not Condensing (%rel) 20 to 80 % rel.							
		Mode of 0	Operation				
SCA-LE-30-03		Speed-c	ontrol by Digital-E	ncoder			
SCA-LS-30-03	Speed-control by voltage	Torque-control		xR-compensation	Speed-control by DC-tacho		

Available Accessories for SCA-L (details see page 36)								
ASO-BM-70-30	ASX-RM-01-01							




# SCA-S: Electrocraft CompletePower™ | Servo Amplifier

Model	Power	Nominal	Quadrants	Operation Mode					
	Supply	Current		Torque Analo Control Pos.	Analog	Speed Control			
	Voltage				Pos.	I x R Comp.	DC-Tacho	Voltage	Encoder
SCA-SE-30-06	11 – 30	6	4						•
SCA-SS-30-06	11 – 30	6	4	•		•	•	•	



#### For Brush-Commutated PMDC Motors. Up to 150 W.

This PWM four-quadrant brushless DC servo amplifier is fully enclosed in a rugged aluminum case which can be panel mounted for easy integration. The drive is available in several configurations depending on your control requirements. The drive handles continuous currents up to 6 Amps and is protected against over-current, over-temperature and motor short-circuit.





SCA-S Specifications										
Model Number	Power Supply Voltage (VDC)	Nominal Current (Amps)	Max. Po Heatsink	wer with (Watts)	Frequency of pov output stage (kF					
SCA-SE-30-06	11 - 30	6	1!	50	50	95				
SCA-SS-30-06	11 30	Ü	,	,,,	30					
	Control Inputs									
	Set value				-10 to +10 VDC; Ri =	: 100 kOhm				
	Tacho				max. 50 VDC; Ri =	50 kOhm				
	Enable				+8 to +30 VDC; Ri	= 5 kOhm				
	Encoder input signals (S	CA-SE only)	Channe	el A & /A; B & /l	B; I & /I; max. 600 kHz ;	TTL/ +5 to +24 VDC; Ri > 10 kOhm				
	Outputs									
	Auxiliary voltage s	source		+3.9 VDC / 20 mA						
	Auxiliary voltage s	source		-3.9 VDC / 20 mA						
	Auxiliary voltage source for end	coder (SCA-SE only)		+5 VDC / 100 mA						
	Auxiliary voltage source	e Enable +V		Connected with 27 kOhm to +VCC						
	Supervision output	t /Error		Open Collector max. +30 VDC; 20 mA						
			Display							
	LEDs				green = OK / red	= Fault				
		Pc	tentiometer	5						
	Function of Potenti	ometer			Gain; nmax; lmax; l	xR; Offset				
		Amk	oient conditio	ons						
	Operation temperat	ture (°C)		-10 to +45						
	Storage temperatu	ıre (°C)		-40 to +85						
	Humidity Range Not Cond	densing (%rel)		20 to 80 % rel.						
Mode of Operation										
SCA-SE-30-06		9	Speed-control by	/ Digital-Encod	er					
SCA-SS-30-06	Speed-control by voltage	e Torque-co	ntrol	IxR-c	ompensation	Speed-control by DC-tacho				

Available Accessories for SCA-S (details see page 36)										
ASO-BM-70-30	ASX-RM-01-01	11 IA210x								



# GO FIGURE.

Customize your options ...

To easily find a motor / motion system that best meets your needs:

Step 1: Select a base technology

Step 2: Select a model type & features

Step 3: Select a performance

Step 4: Select an electrical winding

Step 5: Select any options & accessories



Easily build your own motor at www.configureamotor.com



#### **Build Your Own ElectroCraft Motor**

To Fit Your Exact Application

For the past 60 years, the global team at ElectroCraft has helped engineers like you translate innovative ideas into reality. To build on that legacy, we created this Build-Your-Own ElectroCraft Motor web tool to get you started with our technology.



A web configuration tool from ElectroCraft ... Go Figure! **Your Genius. Our Drive.** 



# **System Matrix - Matching Linear Product and Drive Combinations**

Linear Product			Drive Models							
	Motor P/N		Віро	Bipolar Stepper Drive PMDC Servo Drive						
	Imperial	Metric	SA4505	SA4510	SA4905	DA4303	DA4709	DA4718	SCA-LS-30-03	SCA-SS-30-06
		APPS11M-7A05	•		•					
		APPS11M-7A10	•		•					
		APPS11M-7A15	•		•					
		APPS11M-10A05	•		•					
		APPS11M-10A10	•		•					
		APPS11M-10A15	•		•					
	APPS17-29A10	APPS17M-21A10	•		•					
	APPS17-29A15	APPS17M-21A15	•		•					
	APPS17-29A20	APPS17M-21A20	•		•					
AxialPower	APPS17-47A10	APPS17M-33A10	•		•					
Stepper (APPS)	APPS17-47A15	APPS17M-33A15	•		•					
	APPS17-47A20	APPS17M-33A20	•		•					
	APPS17-58A10	APPS17M-41A10	•		•					
	APPS17-58A15	APPS17M-41A15	•		•					
	APPS17-58A20	APPS17M-41A20	•		•					
	APPS23-90A10	APPS23M-64A10	•		•					
	APPS23-90A20	APPS23M-64A20	•		•					
	APPS23-90A30	APPS23M-64A30	•		•					
	APPS23-150A10	APPS23M-106A10	•		•					
	APPS23-150A20	APPS23M-106A20	•		•					
	APPS23-150A30	APPS23M-106A30	•		•					
126	L3SAF-M200		•		•					
L3-Series <b>Stepper</b>	L3SAF-M300		•		•					
Stepper	L3SAF-M500			•						
	APPD15-10V120	APPD15M-7V120						•		•
AxialPower	APPD15-10V240	APPD15M-7V240				•		•	•	
PMDC (APPD)	APPD25-30V120	APPD25M-21V120						•		
	APPD25-30V240	APPD25M-30V240					•			•











# Other Products available from **ElectroCraft:**

- CompletePower™ I Motion Control
- TorquePower™ I Steppers
- RapidPower™ I BLDC
- DirectPower™ I PMDC
- MobilePower™ I Transmissions
- SolidPower™ Plus I Housed AC
- SurePower™ I C-Frame AC



#### CompletePower™ I Drives



With meticulous engineering and advanced electronics, our CompletePower speed controls and servo drives offer reliability and precision servo motion control. From sensitive medical dosing systems to rugged professional power tools, our CompletePower devices can handle a wide variety of applications.

#### AxialPower™ I Linear Actuator



PMDC, and BLDC motors, our family of AxialPower linear actuators are built to last. Our unique approach to linear motion with low-friction, polymer rotating nuts and stainless steel leadscrews provides high force and linear precision in the smallest packages available.



#### TorquePower™ I Steppers



With non-cumulative position accuracies as low as ±3%, the precision of our TorquePower motor is matched only by the dependability of its performance. Bi-directional operation and enclosed, permanently lubricated ball bearings provide longlasting, smooth operation.

#### RapidPower™ I BLDC



Our BLDC motors provide the rapid acceleration and consistent speed needed for applications from centrifuges to x-y positioning systems. The RapidPower product line ensures a steady operation at any speed by utilizing sealed ball bearings and reduced torque ripple from skewed magnetization.

#### DirectPower™ I PMDC



Dynamically balanced armatures and precision ball bearings ensure that the DirectPower line maintains its characteristically smooth performance. This durable, totally enclosed, nonventilated (TENV) motor is available in a broad product line from lower cost, general purpose options to high performance PMDC servo motors.

#### MobilePower™ I Transmissions



With a choice of output ratios, our MobilePower line of products helps power battery-operated vehicles from wheelchairs to lift trucks. And, to increase durability and decrease noise levels, the robust all metallic gears are hobbed to a precision AGMA 9-Class.

#### SolidPower™ Plus I Housed AC




High starting torques and stator windings matched to your application ensure the SolidPower product provides lasting performance. The dynamically balanced, skewed rotor bars and precision-machined fits keep vibration levels at a minimum.

#### SurePower™ I C-Frame AC



Our AC shaded-pole motor, the SurePower product, can be utilized for a wide range of air-moving applications - perfect for the rigors of refrigeration and commercial food equipment applications.

Toll Free Phone (877) SERV098 Toll Free Fax (877) SERV099 www.electromate.com sales@electromate.com





		Drive_A	Accessories		
			ch Cable		
_	P/N	50cm	100cm	200cm	300cm
	Red	CA2005	CA2010	CA2020	CA2030
1	Yellow	CA4005	CA4010	CA4020	CA4030
	Gray	CA8005	CA8010	CA8020	CA8030
	Aluminium Din Rail l	kit		Braking module	
	Aluminium Din Rail kit with L-shaped bracket for units: SCA-Lx / SCA-Sx (not used for SCA-SS-70-3			Braking module in a rugged aluminium case. DA-Series SCA-Series	P/N ASO-BM-70-30
	Passive heatsink			Passive heatsink	
	Passive heatsink optimized DA43	for drives:		Passive heatsink optimized for SA45 SA49 DA47	or drives:
		P/N HA2008	3		P/N HA3008
	Fanned heatsink			Fanned heatsink	
SVE	One fan heatsink optimize (fan is 1 x 24 VDC, .8 W): DA43	d for drives P/N HA2018		One fan heatsink optimized (fan is 1 x 24 VDC, .8 W): SA45 SA49 DA47	for drives P/N HA3018
	Fanned heatsink			Fanned heatsink	
	Two fan heatsink optimizer (fans are 2 x 24 VDC, .8 W DA43			Two fan heatsink optimized f (fans are 2 x 24 VDC, .8 W): SA45 SA49 DA47	
	Choke module			DIN Rail mounting kit	
	Choke module optimized for Inductance: IA2100 = 2x50 Nominal current: 10 A  DA-Series SCA-Series			DIN Rail mounting kit for uni DA-Series EA-Series	rts: P/N MA0025
	Break Out Board			DIN Rail mounting kit	
	Break Out Board for:  DA-Series EA-Series			DIN Rail mounting kit for: ASO-BM-70-30	
		P/N WA2509	)		P/N MA3050