

ESCON**Feature Comparison Chart**

The ESCON servo controllers are small-sized, powerful 4-quadrant PWM servo controller for the highly efficient control of permanent magnet-activated DC motors.

The featured operating modes – speed control (closed loop), speed control (open loop), and current control – meet the highest requirements. The ESCON servo controllers are designed being commanded by an analog set value and features extensive analog and digital I/O functionality and are being configured via USB interface using the graphical user interface «ESCON Studio» for Windows PCs.

Legend: (✓)* = only in use with DC Tacho or Encoder / nnnnn = order number / ** = details refer to the pin header allocation



| Feature | ESCON Module 24/2 (466023) | ESCON 36/2 DC (403112) | ESCON 36/3 EC (414533) | ESCON Module 50/4 EC-S (446925) | ESCON 50/5 (409510) | ESCON Module 50/5 (438725) | ESCON 70/10 (422969) |
|--|-------------------------------|---------------------------|---------------------------|------------------------------------|-------------------------|-------------------------------|-------------------------|
| Product image | | | | | | | |
| Motors | | | | | | | |
| DC motors up to | 48 W / 144 W | 72 W / 144 W | — | — | 250 W / 750 W | 250 W / 750 W | 700 W / 2'100 W |
| EC motors up to | 48 W / 144 W | — | 97 W / 324 W | 200 W / 600 W | 250 W / 750 W | 250 W / 750 W | 700 W / 2'100 W |
| Sensors | | | | | | | |
| Digital Incremental Encoder (2 channel with or without Line Driver) | ✓ | ✓ | — | — | ✓ | ✓ | ✓ |
| DC Tacho | ✓ | ✓ | — | — | ✓ | ✓ | ✓ |
| Without sensor (DC motors) | ✓ | ✓ | — | — | ✓ | ✓ | ✓ |
| Without sensor (EC motors, sensor-less) | — | — | — | ✓ | — | — | — |
| Digital Hall Sensors (EC motors) | ✓ | — | ✓ | — | ✓ | ✓ | ✓ |
| Electrical Data | | | | | | | |
| Nominal operating voltage +V _{cc} | 10...24 VDC | 10...36 VDC | 10...36 VDC | 10...50 VDC | 10...50 VDC | 10...50 VDC | 10...70 VDC |
| Max. output voltage | 0.98 x +V _{cc} | 0.98 x +V _{cc} | 0.98 x +V _{cc} | 0.96 x +V _{cc} | 0.98 x +V _{cc} | 0.98 x +V _{cc} | 0.95 x +V _{cc} |
| Max. output current | 6 A (<4 s) | 4 A (<60 s) | 9 A (<4 s) | 12 A (<30 s) | 15 A (<20 s) | 15 A (<20 s) | 30 A (<20 s) |
| Continuous output current | 2 A | 2 A | 2.7 A | 4 A | 5 A | 5 A | 10 A |

| Feature | ESCON Module 24/2 (466023) | ESCON 36/2 DC (403112) | ESCON 36/3 EC (414533) | ESCON Module 50/4 EC-S (446925) | ESCON 50/5 (409510) | ESCON Module 50/5 (438725) | ESCON 70/10 (422969) |
|--|--|--|---------------------------|------------------------------------|--|--|--|
| Pulse Width Modulation frequency | 53.6 kHz | | | | | | |
| Sampling rate PI current controller | 53.6 kHz | 53.6 kHz | 53.6 kHz | — | 53.6 kHz | 53.6 kHz | 53.6 kHz |
| Sampling rate PI speed controller | 5.36 kHz | | | | | | |
| Max. efficiency | 92% | 95% | 95% | 97% | 95% | 98% | 98% |
| Max. speed (DC) | limited by max. permissible speed (motor) and max. output voltage (controller) | limited by max. permissible speed (motor) and max. output voltage (controller) | — | — | limited by max. permissible speed (motor) and max. output voltage (controller) | limited by max. permissible speed (motor) and max. output voltage (controller) | limited by max. permissible speed (motor) and max. output voltage (controller) |
| Max. speed (EC; 1 pole pair) | 150'000 rpm | — | 150'000 rpm | 120'000 rpm | 150'000 rpm | 150'000 rpm | 150'000 rpm |
| Built-in motor choke | — | 300 µH; 2 A | 3 x 47 µH; 2.7 A | — | 3 x 30 µH; 5 A | — | 3 x 15 µH; 10 A |
| Inputs / Outputs | | | | | | | |
| Hall sensor signals | H1, H2, H3 | — | H1, H2, H3 | — | H1, H2, H3 | H1, H2, H3 | H1, H2, H3 |
| Encoder signals | A, A\, B, B\ | A, A\, B, B\ | — | — | A, A\, B, B\ | A, A\, B, B\ | A, A\, B, B\ |
| Max. encoder input frequency differential (single-ended) | 1 MHz (100 kHz) | 1 MHz (100 kHz) | — | — | 1 MHz (100 kHz) | 1 MHz (100 kHz) | 1 MHz (100 kHz) |
| Back-EMF signals | — | — | — | BEMF-W1, BEMF-W2, BEMF-W3 | — | — | — |
| Potentiometers | — | 1 | 1 | 1 | 2 | 1 | 2 |
| Digital inputs | 2 | | | | | | |
| Digital inputs/outputs | 2 | | | | | | |
| Analog inputs | 2 | | | | | | |
| Resolution | 12-bit | | | | | | |
| Range | -10...+10 V | | | | | | |
| Circuit | differential | | | | | | |
| Analog outputs | 2 | | | | | | |
| Resolution | 12-bit | | | | | | |
| Range | -4...+4 V | | | | | | |
| Auxiliary voltage output | +5 VDC (IL ≤10 mA) | +5 VDC (IL ≤40 mA) | +5 VDC (IL ≤80 mA) | +5 VDC (IL ≤110 mA) | +5 VDC (IL ≤10 mA) | +5 VDC (IL ≤10 mA) | +5 VDC (IL ≤10 mA) |
| Hall sensor supply voltage | +5 VDC (IL ≤30 mA) | — | +5 VDC (IL ≤30 mA) | — | +5 VDC (IL ≤30 mA) | +5 VDC (IL ≤30 mA) | +5 VDC (IL ≤30 mA) |
| Encoder supply voltage | +5 VDC (IL ≤70 mA) | +5 VDC (IL ≤70 mA) | — | — | +5 VDC (IL ≤70 mA) | +5 VDC (IL ≤70 mA) | +5 VDC (IL ≤70 mA) |
| Status Indicators | Operation: green LED / Error: red LED | | | | | | |

| Feature | ESCON Module 24/2 (466023) | ESCON 36/2 DC (403112) | ESCON 36/3 EC (414533) | ESCON Module 50/4 EC-S (446925) | ESCON 50/5 (409510) | ESCON Module 50/5 (438725) | ESCON 70/10 (422969) |
|--|--|--------------------------------------|------------------------------------|--|---|--|---|
| Connections | | | | | | | |
| J1 Power | Pin header (2.54 mm), 2 poles** | Pin header (2 mm), 2 poles | Pin header (2 mm), 2 poles | Pin header (2.54 mm), 4 poles** | Pluggable screw-type terminal block (3.5 mm), 2 poles | Pin header (2.54 mm), 4 poles** | Pluggable screw-type terminal block (5.0 mm), 2 poles |
| J2 Motor Motor / Hall sensors Motor / BEMF signals | Pin header (2.54 mm), 3 poles** | Pin header (2 mm), 3 poles | Mini module pin header, 8 poles | Pin header (2.54 mm), 9 poles** | Pluggable screw-type terminal block (3.5 mm), 4 poles | Pin header (2.54 mm), 6 poles** | Pluggable screw-type terminal block (5.0 mm), 4 poles |
| J2A Motor Motor / Hall sensors | — | Spring-loaded contacts, 2 poles | Spring-loaded contacts, 8 poles | — | — | — | — |
| J3 Hall sensors | Pin header (2.54 mm), 5 poles** | — | — | — | Pluggable screw-type terminal block (3.5 mm), 5 poles | Pin header (2.54 mm), 5 poles** | Pluggable screw-type terminal block (3.5 mm), 5 poles |
| J4 Encoder | Pin header (2.54 mm), 4 poles** | Pin header (2.54 mm), 5 x 2 poles | — | — | Pin header (2.54 mm), 5 x 2 poles | Pin header (2.54 mm), 4 poles** | Pin header (2.54 mm), 5 x 2 poles |
| J4A Encoder | — | Pin header (1.27 mm), 5 x 2 poles | — | — | — | — | — |
| J5 Digital I/O | Pin header (2.54 mm), 5 poles** | Pin header (2 mm), 6 poles | Pin header (2 mm), 6 poles | Pin header (2.54 mm), 5 poles** | Pluggable screw-type terminal block (3.5 mm), 6 poles | Pin header (2.54 mm), 5 poles** | Pluggable screw-type terminal block (3.5 mm), 6 poles |
| J6 Analog I/O | Pin header (2.54 mm), 6 poles** | Pin header (2 mm), 7 poles | Pin header (2 mm), 7 poles | Pin header (2.54 mm), 6 poles** | Pluggable screw-type terminal block (3.5 mm), 7 poles | Pin header (2.54 mm), 6 poles** | Pluggable screw-type terminal block (3.5 mm), 7 poles |
| J7 USB | USB Type micro B female | | | | | | |
| Mechanical Data | | | | | | | |
| Weight (approximate) | 7 g | 30 g | 36 g | 11 g | 204 g | 12 g | 259 g |
| Dimensions (L x W x H) | 35.6 x 26.7 x 12.7 mm | 55 x 40 x 16.1 mm | 55 x 40 x 19.8 mm | 43.2 x 31.8 x 12.7 mm | 115 x 75.5 x 24 mm | 43.2 x 31.8 x 12.7 mm | 125 x 78.5 x 27 mm |
| Mounting | Pluggable (female headers RM 2.54 mm) | M2.5 screws | M2.5 screws | Pluggable (female headers RM 2.54 mm) | M4 screws | Pluggable (female headers RM 2.54 mm) | M4 screws |

| Feature | ESCON Module 24/2 (466023) | ESCON 36/2 DC (403112) | ESCON 36/3 EC (414533) | ESCON Module 50/4 EC-S (446925) | ESCON 50/5 (409510) | ESCON Module 50/5 (438725) | ESCON 70/10 (422969) |
|---|--------------------------------------|--|--|--------------------------------------|--|--|--|
| Environmental Conditions | | | | | | | |
| Temperature – Operation | -30...+60 °C | -30...+45 °C | -30...+45 °C | -30...+45 °C | -30...+45 °C | -30...+45 °C | -30...+45 °C |
| Temperature – Extended range | +60...+80 °C; Derating: -0.1 A/°C | +45...+81 °C; Derating: -0.056 A/°C | +45...+78 °C; Derating: -0.082 A/°C | +45...+65 °C; Derating: -0.2 A/°C | +45...+85 °C; Derating: -0.111 A/°C | +45...+75 °C; Derating: -0.167 A/°C | +45...+82 °C; Derating: -0.270 A/°C |
| Temperature – Storage | | | | -40...+85 °C | | | |
| Altitude – Operation | 0...6'000 m MSL | 0...6'000 m MSL | 0...6'000 m MSL | 0...6'000 m MSL | 0...10'000 m MSL | 0...6'000 m MSL | 0...10'000 m MSL |
| Altitude – Extended range (Derating: see Hardware Reference) | 6'000...10'000 m MSL | 6'000...10'000 m MSL | 6'000...10'000 m MSL | 6'000...10'000 m MSL | — | 6'000...10'000 m MSL | — |
| Humidity (condensation not permitted) | | | | 5...90% | | | |
| Functionality | | | | | | | |
| Operating Mode | | | | | | | |
| Current controller (torque control) | ✓ | ✓ | ✓ | — | ✓ | ✓ | ✓ |
| Speed controller (closed loop) | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| with encoder feedback | ✓ | ✓ | — | — | ✓ | ✓ | ✓ |
| with DC Tacho feedback | ✓ | ✓ | — | — | ✓ | ✓ | ✓ |
| with Hall sensor feedback | ✓ | — | ✓ | — | ✓ | ✓ | ✓ |
| with BEMF feedback | — | — | — | ✓ | — | — | — |
| Speed controller (open loop) | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| with static IxR Compensation | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| with adaptive IxR Compensation | ✓ | (✓)* | ✓ | ✓ | ✓ | ✓ | ✓ |
| Set Value | | | | | | | |
| Analog set value | | | | ✓ | | | |
| PWM set value | | | | ✓ | | | |
| RC Servo set value | | | | ✓ | | | |
| Fixed set value | | | | ✓ | | | |
| 2 fixed set values | | | | ✓ | | | |

| Feature | ESCON Module 24/2 (466023) | ESCON 36/2 DC (403112) | ESCON 36/3 EC (414533) | ESCON Module 50/4 EC-S (446925) | ESCON 50/5 (409510) | ESCON Module 50/5 (438725) | ESCON 70/10 (422969) |
|------------------------------------|-------------------------------|---------------------------|---------------------------|------------------------------------|------------------------|-------------------------------|-------------------------|
| Digital I/O Functionality | | | | | | | |
| Enable | | | | ✓ | | | |
| Enable CW | | | | ✓ | | | |
| Enable CCW | | | | ✓ | | | |
| Enable CW + CCW | | | | ✓ | | | |
| Enable + Direction | | | | ✓ | | | |
| Stop | | | | ✓ | | | |
| Ready | | | | ✓ | | | |
| Speed Comparator | | | | ✓ | | | |
| Current Comparator | | | | ✓ | | | |
| Commutation frequency | ✓ | — | ✓ | ✓ | ✓ | ✓ | ✓ |
| Monitoring Outputs | | | | | | | |
| Monitor Current | | | | ✓ | | | |
| Monitor Speed | | | | ✓ | | | |
| Analog Settings | | | | | | | |
| Set value | | | | ✓ | | | |
| Current limit | | | | ✓ | | | |
| Offset adjust set value | | | | ✓ | | | |
| Speed ramp | | | | ✓ | | | |
| Current gain (using potentiometer) | — | ✓ | ✓ | — | ✓ | ✓ | ✓ |
| Speed gain (using potentiometer) | — | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| IxR Factor (using potentiometer) | — | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Protection | | | | | | | |
| Overcurrent | | | | ✓ | | | |
| Current limiter (adjustable) | | | | ✓ | | | |
| Thermal overload | | | | ✓ | | | |
| Undervoltage | | | | ✓ | | | |
| Oversupply | | | | ✓ | | | |
| Voltage transients | | | | ✓ | | | |
| Short-circuit of motor winding | | | | ✓ | | | |

| Feature | ESCON Module 24/2 (466023) | ESCON 36/2 DC (403112) | ESCON 36/3 EC (414533) | ESCON Module 50/4 EC-S (446925) | ESCON 50/5 (409510) | ESCON Module 50/5 (438725) | ESCON 70/10 (422969) |
|--------------------------|--|---------------------------|---------------------------|------------------------------------|------------------------|-------------------------------|-------------------------|
| Software | | | | | | | |
| Installation Program | ESCON Setup | | | | | | |
| Graphical User Interface | ESCON Studio | | | | | | |
| Startup Wizard | | | | ✓ | | | |
| Regulation Tuning | | | | ✓ | | | |
| Diagnostics | | | | ✓ | | | |
| Firmware Update | | | | ✓ | | | |
| Controller Monitor | | | | ✓ | | | |
| Parameters | | | | ✓ | | | |
| Data Recording | | | | ✓ | | | |
| Online Help | | | | ✓ | | | |
| Language | German, English, French, Italian, Spanish, Japanese, Chinese | | | | | | |
| Operating System | Windows 10, 8, 7, XP SP3 | | | | | | |
| Communication interface | USB 2.0 / USB 3.0 (full speed) | | | | | | |

| Feature | ESCON Module 24/2 (466023) | ESCON 36/2 DC (403112) | ESCON 36/3 EC (414533) | ESCON Module 50/4 EC-S (446925) | ESCON 50/5 (409510) | ESCON Module 50/5 (438725) | ESCON 70/10 (422969) |
|---|-------------------------------|---------------------------|---------------------------|------------------------------------|------------------------|-------------------------------|-------------------------|
| Accessories (not included in delivery) | | | | | | | |
| 418719 Adapter BLACK FPC11poles | — | — | ✓ | — | — | — | — |
| 418723 Adapter BLUE FPC8poles | — | — | ✓ | — | — | — | — |
| 418721 Adapter GREEN FPC8poles | — | — | ✓ | — | — | — | — |
| 403962 DC Motor Cable | — | ✓ | — | — | — | — | — |
| 275934 Encoder Cable | — | ✓ | — | — | ✓ | — | ✓ |
| 404404 ESCON 36/2 DC Connector Set | — | ✓ | — | — | — | — | — |
| 425255 ESCON 36/3 EC Connector Set | — | — | ✓ | — | — | — | — |
| 486400 ESCON Module 24/2 Motherboard | ✓ | — | — | — | — | — | — |
| 438779 ESCON Module Motherboard | — | — | — | — | — | ✓ | — |
| 450237 ESCON Module Motherboard Sensorless | — | — | — | ✓ | — | — | — |
| 409286 ESCON USB Stick | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| 403965 I/O Cable 6core (Digital I/Os) | — | ✓ | ✓ | — | — | — | — |
| 403964 I/O Cable 7core (Analog I/Os) | — | ✓ | ✓ | — | — | — | — |
| 403957 Power Cable | — | ✓ | ✓ | — | — | — | — |
| 403968 USB Type A - micro B Cable | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |

Windows®: © Microsoft Corporation, USA-Redmond, WA